

VLT® Soft Starter MCD 500



The perfect solution, also for more severe applications:

- Pumps
- Conveyors
- Fans
- Mixers
- Compressors
- Centrifuge
- Mill
- Saw
- · And many more

Power range

21 – 1600 Å, 7,5 – 800 kW (1,2 MW inside Delta Connection) Versions for 200 – 690 VAC



VLT® Soft Starter MCD 500 is a total motor starting solution. Current transformers measure motor current and provide feedback for controlled motor ramp profiles.

AAC, the Adaptive Acceleration Control automatically employs the best starting and stopping profile for the application.


Adaptive Acceleration Control means, that for each start and stop, the soft starter compares and adapts the process to the chosen profile fitting to the application.

The VLT® Soft Starter MCD 500 has a four line graphical display and a logic keypad making programming easy. Advanced setup is possible displaying operational status.

Three menu systems: Quick Menu, Application Setup and Main Menu provide optimum programming approach.

| Features | Benefits |
|--|--|
| AAC Adaptive Acceleration Control | Automatically adapts to the best starting and stopping profile for the application |
| Adjustable Bus Bars, allow for top, bottom or both (>=360A) | Space saving, reduced cable cost and easy retrofitting |
| DC injection braking distributed evenly over three phases | Reduced installation cost and less stress on the motor |
| Inside Delta (6-wire connection) | Smaller soft starter can be selected for the application |
| • Log Menus, 99 Events and Trip log provide information on events, trips and performance | Eases analysis on the application |
| Auto Reset | Less down time |
| Jog (slow-speed operation) | Application flexibility |
| Second-order thermal model | Allows motor to be used to its full potential without damage from overloading |
| • Internal bypass contactors (<= 110kW) | Saves space and wiring compared to external bypass Very little heat dissipates when running. Eliminates costly external fans, wiring or bypass contactors |
| Auto-start/stop clock | Application flexibility |
| Compact size – amongst the smallest in their class | Saves space in cabinets and other application setups |
| 4-line graphical display | Optimum programming approach and setup for viewing operational status |
| Multiple programming setup (Standard Menu, Extended Menu, Quick Set) | Simplifies the programming, but still holding to maximum flexibility |
| Multiple (8) languages | Serving the whole world |





Fully featured Soft Starter for motors up to 800 kW

- Total motor starting solution
- Advanced start, stop and protection features
- Adaptive Acceleration Control
- Inside Delta connection
- 4 line graphical display
- Multiple programming setup menus

Optional:

- Modules for serial communication:
 - DeviceNet
 - Profibus
 - Modbus RTU
 - USB
- · Remote operator kit
- PC software



Remote operation kit

- · Start/stop, reset
- LED for start, run, trip
- Trip codes
- Current display
- Motor temperature display
- 4 20 mA output



Specifications

| • | | |
|-----------------------------------|--|--|
| Supply | | |
| Mains voltage (L1, L2, L3) | | |
| MCD5-xxxx-T5 | 200 VAC ~ 525 VAC (± 10%) | |
| MCD5-xxxx-T7 | 380 VAC ~ 690 VAC (± 10%) (earthed star supply system only) | |
| MCD5-xxxx-T7 | 380 VAC ~ 600 VAC (± 10%) (inside delta connection) | |
| Control voltage (A4, A5, A6) | | |
| CV1 (A5, A6) | 24 VAC/VDC (± 20%) | |
| CV2 (A5, A6) | 110~120 VAC (+ 10% / - 15%) | |
| CV2 (A4, A6) | 220~240 VAC (+ 10% / - 15%) | |
| Mains frequency | 50/60 Hz (± 10%) | |
| Rated insulation voltage to earth | 600 VAC | |
| Rated impulse withstand voltage | 4 kV | |
| Form designation | Bypassed or continuous, semiconductor motor starter form 1 | |

| Short circuit capability | |
|---------------------------------------|----------------------------|
| Coordination with semiconductor fuses | Type 2 |
| Coordination with HRC fuses | Type 1 |
| MCD5-0021B to MCD5-0105B | prospective current 10 kA |
| MCD5-0131B to MCD5-0245C | prospective current 18 kA |
| MCD5-0360C to MCD5-0927C | prospective current 85 kA |
| MCD5-1200C to MCD5-1600C | prospective current 100 kA |

| Electromagnetic capability (compliant with EU Directive 89/336/EEC) | |
|---|--|
| EMC Emissions(Terminals 13 & 14) | IEC 60947-4-2 Class B and Lloyds Marine No. 1 Specification |
| EMC Immunity | IEC 60947-4-2 |

| Outputs | |
|-------------------------------------|--|
| Relay Outputs | 10A @ 250 VAC resistive, 5A @ 250 VAC AC15 pf 0.3 |
| Programmable Outputs | |
| Relay A (13, 14) | Normally open |
| Relay B (21, 22, 24) | Changeover |
| Relay C (33, 34) | Normally open |
| Analog Output (07, 08) | 0 – 20 mA or 4 – 20 mA (selectable) |
| Maximum load | 600 Ω (12 VDC @ 20 mA) (accuracy ±5%) |
| 24 VDC Output (16, 08) Maximum load | 200 mA (accuracy ± 10%) |

| erating |
|---------|
| |
| ng |
| |
| |
| |

| Pollution degree | Pollution Degree 3 | Pollution Degree 3 | |
|------------------|----------------------|--------------------|--|
| Heat Dissipation | | | |
| During start | 4.5 watts per ampere | | |

Dimensions

| Current rating [A] | Weight [kg] | Height [mm] | Width [mm] | Depth [mm] |
|-----------------------|-------------|-------------|------------|------------|
| 21, 37, 43 and 53 | 4.2 | | | |
| 68 | 4.5 | 295 | 150 | 183 |
| 84, 89 and 105 | 4.9 | | | |
| 131, 141, 195 and 215 | 14.9 | 438 | 275 | 250 |
| 245 | 23.9 | 460 | 390 | 279 |
| 360, 380 and 428 | 50.1 | 689 | 430 | 302 |
| 595, 619, 790 and 927 | 53.1 | | 430 | 302 |
| 1200, 1410 and 1600 | 120 | 856 | 585 | 364 |

Danfoss can accept no responsibility for possible errors in catalogues, brochures and other printed material. Danfoss reserves the right to alter its products without notice. This also applies to products already on order provided that such alterations can be made without subsequential changes being necessary in specifications already agreed.

All trademarks in this material are property of the respective companies. Danfoss and the Danfoss logotype are trademarks of Danfoss A/S. All rights reserved.